SIEMENS

Data sheet

6ES7211-0AA23-0XB0



Figure similar

 *** spare part *** SIMATIC S7-200, CPU 221 Compact unit, DC power supply 6 DI DC/4 DO DC 4 KB progr./2 KB data

Supply voltage	
Rated value (DC)	
• 24 V DC	Yes
Load voltage L+	
 Rated value (DC) 	24 V
 permissible range, lower limit (DC) 	20.4 V
 permissible range, upper limit (DC) 	28.8 V
Input current	
Inrush current, max.	10 A; at 28.8 V
from supply voltage L+, max.	450 mA; 80 to 450 mA
Encoder supply	
24 V encoder supply	
• 24 V	Yes; permissible range: 15.4 to 28.8 V
 Short-circuit protection 	Yes; electronic at 600 mA
 Output current, max. 	180 mA
Power loss	
Power loss, typ.	3 W
Memory	
Number of memory modules (optional)	1; pluggable memory module, content identical with integral EEPROM; can additionally store recipes, data logs and other files
Work memory	
integrated (for program)	4 kbyte
integrated (for data)	2 kbyte
Backup	
• present	Yes; Program: Entire program maintenance-free on integral EEPROM, programmable via CPU; data: Entire DB 1 loaded from PG/PC maintenance-free on integral EEPROM, current values of DB 1 in RAM, retentive memory bits, timers, counters, etc. maintenance-free via high-performance capacitor; optional battery for long-term buffering
Battery	
Backup battery	
Backup time, max.	50 h; (min. 8 h at 40 °C); 200 days (typ.) with optional battery module
CPU processing times	
for bit operations, max.	0.22 µs
Counters, timers and their retentivity	
S7 counter	
Number	256
Retentivity	
— adjustable	Yes; via high-performance capacitor or battery
— lower limit	1

— upper limit	256
Counting range	
— lower limit	0
— upper limit	32 767
S7 times	
Number	256
Retentivity	Vaccinia high marfarmanas aspasitas as hattas:
— adjustable	Yes; via high-performance capacitor or battery
— upper limit	64
Time range — lower limit	1 ms
— upper limit	54 min; 4 timers: 1 ms to 30 s; 16 timers: 10 ms to 5 min; 236 timers: 100 ms to
— аррег шик	54 min 54 min 55 min 65 56 57 min 65 56 57 min 65 57 min
Data areas and their retentivity	
Flag	
• Size, max.	32 byte
Retentivity available	Yes; M 0.0 to M 31.7
 of which retentive with battery 	0 to 255, via high-performance capacitor or battery, adjustable
 of which retentive without battery 	0 to 112 in EEPROM, adjustable
Hardware configuration	
connectable programming devices/PCs	SIMATIC PG/PC, standard PC
Digital inputs	
Number of digital inputs	6; Integrated
Source/sink input	Yes; optionally, per group
Input voltage	
Rated value (DC)	24 V
● for signal "0"	0 to 5 V
• for signal "1"	min. 15 V
Input current	
• for signal "1", typ.	2.5 mA
Input delay (for rated value of input voltage)	
for standard inputs	V
— parameterizable	Yes; all
— at "0" to "1", min.	0.2 ms
— at "0" to "1", max.	12.8 ms
for interrupt inputs	V 1001 100
— parameterizable	Yes; I 0.0 to I 0.3
for technological functions	Voc. /E 0.0 to E 0.5) 20 kHz
— parameterizable Cable length	Yes; (E 0.0 to E 0.5) 30 kHz
• shielded, max.	500 m; Standard input: 500 m, high-speed counters: 50 m
• unshielded, max.	300 m; not for high-speed signals
Digital outputs	ooo iii, not or nigri speed signals
Number of digital outputs	4; Transistor
Short-circuit protection	No; to be provided externally
Limitation of inductive shutdown voltage to	1 W
Switching capacity of the outputs	
with resistive load, max.	0.75 A
• on lamp load, max.	5 W
Output voltage	
• for signal "1", min.	20 V DC
Output current	
• for signal "1" rated value	750 mA
• for signal "0" residual current, max.	0.1 mA
Output delay with resistive load	
• "0" to "1", max.	15 μ s; of the standard outputs, max. (Q0.2 to Q0.3) 15 μ s; of the pulse outputs,
	max. (Q0.0 to Q0.1) 2 µs
• "1" to "0", max.	130 μs; of the standard outputs, max. (Q0.2 to Q0.3) 100 μs; of the pulse outputs, max. (Q0.0 to Q0.1) 10 μs
	σαιραίο, παλ. (ασίσ ασίτ) το μο
Parallel switching of two outputs	
Parallel switching of two outputs • for uprating	Yes

Custobing fraguency	
Switching frequency	20 kHz; 00 0 to 00 1
of the pulse outputs, with resistive load, max. Total current of the outputs (per group)	20 kHz; Q0.0 to Q0.1
all mounting positions	
— up to 40 °C, max.	3 A
— up to 40°C, max. horizontal installation	
— up to 55 °C, max.	3 A
Relay outputs	
Number of relay outputs	0
Cable length	
• shielded, max.	500 m
• unshielded, max.	150 m
Analog inputs	
Number of analog potentiometers	1; Analog potentiometer; resolution 8 bit
Encoder	
Connectable encoders	
• 2-wire sensor	Yes
— permissible quiescent current (2-wire sensor), max.	1 mA
1. Interface	
Interface type	Integrated RS 485 interface
Protocols	
• MPI	Yes; As MPI slave for data exchange with MPI masters (S7-300/S7-400 CPUs, OPs, TDs, Push Button Panels); S7-200-internal CPU/CPU communication is possible in the MPI network with restrictions; transmission rates: 19.2/187.5 kbit/s
• PPI	Yes; with PPI protocol for program functions, HMI functions (TD 200, OP), S7-200-internal CPU/CPU communication; transmission rates 9.6/19.2/187.5 kbit/s
serial data exchange	Yes; As freely programmable interface with interrupt facility for serial data exchange with third-party devices with ASCII protocol transfer rates: 1.2 / 2.4 / 4.8 / 9.6 / 19.2 / 38.4 / 57.6 / 115.2 kbps; the PC/PPI cable can also be used as RS 232/RS 485 converter
MPI	
• Transmission rate, min.	19.2 kbit/s
Transmission rate, max.	187.5 kbit/s
Integrated Functions	
Integrated Functions Counter Number of counters	4; High-speed counters (30 kHz each), 32 bit (incl. sign), can be used as up/down counters or for connecting 2 incremental encoders with 2 pulse trains offset by 90° (max. 20 kHz (A/B counters)); parameterizable enable and reset input; interrupt facilities (incl. call of subroutine with any content) when the setpoint is reached; reversal in counting direction, etc.
Counter • Number of counters • Counting frequency, max.	up/down counters or for connecting 2 incremental encoders with 2 pulse trains offset by 90° (max. 20 kHz (A/B counters)); parameterizable enable and reset input; interrupt facilities (incl. call of subroutine with any content) when the setpoint is reached; reversal in counting direction, etc. 30 kHz
Counter Number of counters Counting frequency, max. Number of alarm inputs	up/down counters or for connecting 2 incremental encoders with 2 pulse trains offset by 90° (max. 20 kHz (A/B counters)); parameterizable enable and reset input; interrupt facilities (incl. call of subroutine with any content) when the setpoint is reached; reversal in counting direction, etc. 30 kHz 4; 4 rising edges and/or 4 falling edges
Counter • Number of counters • Counting frequency, max.	up/down counters or for connecting 2 incremental encoders with 2 pulse trains offset by 90° (max. 20 kHz (A/B counters)); parameterizable enable and reset input; interrupt facilities (incl. call of subroutine with any content) when the setpoint is reached; reversal in counting direction, etc. 30 kHz 4; 4 rising edges and/or 4 falling edges 2; High-speed outputs, 20 kHz, with interrupt option; pulse-width and frequency
Counter Number of counters Counting frequency, max. Number of alarm inputs Number of pulse outputs	up/down counters or for connecting 2 incremental encoders with 2 pulse trains offset by 90° (max. 20 kHz (A/B counters)); parameterizable enable and reset input; interrupt facilities (incl. call of subroutine with any content) when the setpoint is reached; reversal in counting direction, etc. 30 kHz 4; 4 rising edges and/or 4 falling edges
Counter Number of counters Counting frequency, max. Number of alarm inputs Number of pulse outputs Limit frequency (pulse)	up/down counters or for connecting 2 incremental encoders with 2 pulse trains offset by 90° (max. 20 kHz (A/B counters)); parameterizable enable and reset input; interrupt facilities (incl. call of subroutine with any content) when the setpoint is reached; reversal in counting direction, etc. 30 kHz 4; 4 rising edges and/or 4 falling edges 2; High-speed outputs, 20 kHz, with interrupt option; pulse-width and frequency modulation option
Counter Number of counters Counting frequency, max. Number of alarm inputs Number of pulse outputs Limit frequency (pulse) Potential separation	up/down counters or for connecting 2 incremental encoders with 2 pulse trains offset by 90° (max. 20 kHz (A/B counters)); parameterizable enable and reset input; interrupt facilities (incl. call of subroutine with any content) when the setpoint is reached; reversal in counting direction, etc. 30 kHz 4; 4 rising edges and/or 4 falling edges 2; High-speed outputs, 20 kHz, with interrupt option; pulse-width and frequency modulation option
Counter Number of counters Counting frequency, max. Number of alarm inputs Number of pulse outputs Limit frequency (pulse)	up/down counters or for connecting 2 incremental encoders with 2 pulse trains offset by 90° (max. 20 kHz (A/B counters)); parameterizable enable and reset input; interrupt facilities (incl. call of subroutine with any content) when the setpoint is reached; reversal in counting direction, etc. 30 kHz 4; 4 rising edges and/or 4 falling edges 2; High-speed outputs, 20 kHz, with interrupt option; pulse-width and frequency modulation option 20 kHz
Counter Number of counters Counting frequency, max. Number of alarm inputs Number of pulse outputs Limit frequency (pulse) Potential separation Potential separation digital inputs	up/down counters or for connecting 2 incremental encoders with 2 pulse trains offset by 90° (max. 20 kHz (A/B counters)); parameterizable enable and reset input; interrupt facilities (incl. call of subroutine with any content) when the setpoint is reached; reversal in counting direction, etc. 30 kHz 4; 4 rising edges and/or 4 falling edges 2; High-speed outputs, 20 kHz, with interrupt option; pulse-width and frequency modulation option
Counter • Number of counters • Counting frequency, max. Number of alarm inputs Number of pulse outputs Limit frequency (pulse) Potential separation Potential separation digital inputs • between the channels	up/down counters or for connecting 2 incremental encoders with 2 pulse trains offset by 90° (max. 20 kHz (A/B counters)); parameterizable enable and reset input; interrupt facilities (incl. call of subroutine with any content) when the setpoint is reached; reversal in counting direction, etc. 30 kHz 4; 4 rising edges and/or 4 falling edges 2; High-speed outputs, 20 kHz, with interrupt option; pulse-width and frequency modulation option 20 kHz
Counter • Number of counters • Counting frequency, max. Number of alarm inputs Number of pulse outputs Limit frequency (pulse) Potential separation Potential separation digital inputs • between the channels • between the channels, in groups of	up/down counters or for connecting 2 incremental encoders with 2 pulse trains offset by 90° (max. 20 kHz (A/B counters)); parameterizable enable and reset input; interrupt facilities (incl. call of subroutine with any content) when the setpoint is reached; reversal in counting direction, etc. 30 kHz 4; 4 rising edges and/or 4 falling edges 2; High-speed outputs, 20 kHz, with interrupt option; pulse-width and frequency modulation option 20 kHz
Counter • Number of counters • Counting frequency, max. Number of alarm inputs Number of pulse outputs Limit frequency (pulse) Potential separation Potential separation digital inputs • between the channels • between the channels, in groups of Potential separation digital outputs	up/down counters or for connecting 2 incremental encoders with 2 pulse trains offset by 90° (max. 20 kHz (A/B counters)); parameterizable enable and reset input; interrupt facilities (incl. call of subroutine with any content) when the setpoint is reached; reversal in counting direction, etc. 30 kHz 4; 4 rising edges and/or 4 falling edges 2; High-speed outputs, 20 kHz, with interrupt option; pulse-width and frequency modulation option 20 kHz Yes 2 and 4
Counter • Number of counters • Counting frequency, max. Number of alarm inputs Number of pulse outputs Limit frequency (pulse) Potential separation Potential separation digital inputs • between the channels • between the channels, in groups of Potential separation digital outputs • between the channels	up/down counters or for connecting 2 incremental encoders with 2 pulse trains offset by 90° (max. 20 kHz (A/B counters)); parameterizable enable and reset input; interrupt facilities (incl. call of subroutine with any content) when the setpoint is reached; reversal in counting direction, etc. 30 kHz 4; 4 rising edges and/or 4 falling edges 2; High-speed outputs, 20 kHz, with interrupt option; pulse-width and frequency modulation option 20 kHz Yes 2 and 4 Yes; Optocoupler
Counter • Number of counters • Counting frequency, max. Number of alarm inputs Number of pulse outputs Limit frequency (pulse) Potential separation Potential separation digital inputs • between the channels • between the channels, in groups of Potential separation digital outputs • between the channels • between the channels • between the channels • between the channels, in groups of	up/down counters or for connecting 2 incremental encoders with 2 pulse trains offset by 90° (max. 20 kHz (A/B counters)); parameterizable enable and reset input; interrupt facilities (incl. call of subroutine with any content) when the setpoint is reached; reversal in counting direction, etc. 30 kHz 4; 4 rising edges and/or 4 falling edges 2; High-speed outputs, 20 kHz, with interrupt option; pulse-width and frequency modulation option 20 kHz Yes 2 and 4 Yes; Optocoupler
Counter • Number of counters • Counting frequency, max. Number of alarm inputs Number of pulse outputs Limit frequency (pulse) Potential separation Potential separation digital inputs • between the channels • between the channels, in groups of Potential separation digital outputs • between the channels • between the channels • between the channels • between the channels • between the channels, in groups of Permissible potential difference	up/down counters or for connecting 2 incremental encoders with 2 pulse trains offset by 90° (max. 20 kHz (A/B counters)); parameterizable enable and reset input; interrupt facilities (incl. call of subroutine with any content) when the setpoint is reached; reversal in counting direction, etc. 30 kHz 4; 4 rising edges and/or 4 falling edges 2; High-speed outputs, 20 kHz, with interrupt option; pulse-width and frequency modulation option 20 kHz Yes 2 and 4 Yes; Optocoupler
Counter • Number of counters • Counting frequency, max. Number of alarm inputs Number of pulse outputs Limit frequency (pulse) Potential separation Potential separation digital inputs • between the channels • between the channels, in groups of Potential separation digital outputs • between the channels • between the channels • between the channels • between the channels, in groups of Permissible potential difference between different circuits	up/down counters or for connecting 2 incremental encoders with 2 pulse trains offset by 90° (max. 20 kHz (A/B counters)); parameterizable enable and reset input; interrupt facilities (incl. call of subroutine with any content) when the setpoint is reached; reversal in counting direction, etc. 30 kHz 4; 4 rising edges and/or 4 falling edges 2; High-speed outputs, 20 kHz, with interrupt option; pulse-width and frequency modulation option 20 kHz Yes 2 and 4 Yes; Optocoupler
Counter • Number of counters • Counting frequency, max. Number of alarm inputs Number of pulse outputs Limit frequency (pulse) Potential separation Potential separation digital inputs • between the channels • between the channels, in groups of Potential separation digital outputs • between the channels • between the channels • between the channels • between the channels • between the channels, in groups of Permissible potential difference between different circuits Degree and class of protection	up/down counters or for connecting 2 incremental encoders with 2 pulse trains offset by 90° (max. 20 kHz (A/B counters)); parameterizable enable and reset input; interrupt facilities (incl. call of subroutine with any content) when the setpoint is reached; reversal in counting direction, etc. 30 kHz 4; 4 rising edges and/or 4 falling edges 2; High-speed outputs, 20 kHz, with interrupt option; pulse-width and frequency modulation option 20 kHz Yes 2 and 4 Yes; Optocoupler 4 500 V DC between 24 V DC and 5 V DC
Counter • Number of counters • Counting frequency, max. Number of alarm inputs Number of pulse outputs Limit frequency (pulse) Potential separation Potential separation digital inputs • between the channels • between the channels, in groups of Potential separation digital outputs • between the channels • between the channels • between the channels • between the channels • between the channels, in groups of Permissible potential difference between different circuits Degree and class of protection IP degree of protection	up/down counters or for connecting 2 incremental encoders with 2 pulse trains offset by 90° (max. 20 kHz (A/B counters)); parameterizable enable and reset input; interrupt facilities (incl. call of subroutine with any content) when the setpoint is reached; reversal in counting direction, etc. 30 kHz 4; 4 rising edges and/or 4 falling edges 2; High-speed outputs, 20 kHz, with interrupt option; pulse-width and frequency modulation option 20 kHz Yes 2 and 4 Yes; Optocoupler 4 500 V DC between 24 V DC and 5 V DC
Counter • Number of counters • Counting frequency, max. Number of alarm inputs Number of pulse outputs Limit frequency (pulse) Potential separation Potential separation digital inputs • between the channels • between the channels, in groups of Potential separation digital outputs • between the channels • between the channels • between the channels • between the channels, in groups of Permissible potential difference between different circuits Degree and class of protection IP degree of protection Ambient conditions	up/down counters or for connecting 2 incremental encoders with 2 pulse trains offset by 90° (max. 20 kHz (A/B counters)); parameterizable enable and reset input; interrupt facilities (incl. call of subroutine with any content) when the setpoint is reached; reversal in counting direction, etc. 30 kHz 4; 4 rising edges and/or 4 falling edges 2; High-speed outputs, 20 kHz, with interrupt option; pulse-width and frequency modulation option 20 kHz Yes 2 and 4 Yes; Optocoupler 4 500 V DC between 24 V DC and 5 V DC
Counter • Number of counters • Counting frequency, max. Number of alarm inputs Number of pulse outputs Limit frequency (pulse) Potential separation Potential separation digital inputs • between the channels • between the channels, in groups of Potential separation digital outputs • between the channels • between the channels • between the channels • between the channels • between the channels, in groups of Permissible potential difference between different circuits Degree and class of protection IP degree of protection Ambient conditions Ambient temperature during operation	up/down counters or for connecting 2 incremental encoders with 2 pulse trains offset by 90° (max. 20 kHz (A/B counters)); parameterizable enable and reset input; interrupt facilities (incl. call of subroutine with any content) when the setpoint is reached; reversal in counting direction, etc. 30 kHz 4; 4 rising edges and/or 4 falling edges 2; High-speed outputs, 20 kHz, with interrupt option; pulse-width and frequency modulation option 20 kHz Yes 2 and 4 Yes; Optocoupler 4 500 V DC between 24 V DC and 5 V DC
Counter Number of counters Counting frequency, max. Number of alarm inputs Number of pulse outputs Limit frequency (pulse) Potential separation Potential separation digital inputs between the channels between the channels, in groups of Potential separation digital outputs between the channels between the channels between the channels, in groups of Permissible potential difference between different circuits Degree and class of protection IP degree of protection Ambient conditions Ambient temperature during operation horizontal installation, min.	up/down counters or for connecting 2 incremental encoders with 2 pulse trains offset by 90° (max. 20 kHz (A/B counters)); parameterizable enable and reset input; interrupt facilities (incl. call of subroutine with any content) when the setpoint is reached; reversal in counting direction, etc. 30 kHz 4; 4 rising edges and/or 4 falling edges 2; High-speed outputs, 20 kHz, with interrupt option; pulse-width and frequency modulation option 20 kHz Yes 2 and 4 Yes; Optocoupler 4 500 V DC between 24 V DC and 5 V DC

Air management and the UEO 00000 0 40		
Air pressure acc. to IEC 60068-2-13	20018	
 permissible range, lower limit 	860 hPa	
permissible range, upper limit	1 080 hPa	
Relative humidity		
 Operation, min. 	5 %	
 Operation, max. 	95 %; RH class 2 in accordance with IEC 1131-2	
configuration / header		
configuration / programming / header		
Command set	Bit logic instructions, compare instructions, timer instructions, counter instructions, clock instructions, transmissions instructions, table instructions, logic instructions, shift and rotate instructions, conversion instructions, program control instructions, interrupt and communications instructions, logic stack instructions, integer maths, floating-point math instructions, numerical functions	
 Program processing 	free cycle (OB 1), interrupt-controller, time-controlled (1 to 255 ms)	
 Program organization 	1 OB, 1 DB, 1 SDB subroutines with/without parameter transfer	
 Number of subroutines, max. 	64	
Programming language		
— LAD	Yes	
— FBD	Yes	
— STL	Yes	
Know-how protection		
 User program protection/password protection 	Yes; 3-stage password protection	
connection method		
Plug-in I/O terminals	No	
Dimensions		
Width	90 mm	
Height	80 mm	
Depth	62 mm	
Weights		
Weight, approx.	270 g	
-		

3/12/2021

last modified: