



### Ordering data

6SL3210-5BE24-0UV0

Client order no. :

Order no. :

Offer no. :

Remarks :

Item no. :

Consignment no. :

Project :

Rated data		General tech. specifications	
<b>Input</b>		<b>Power factor <math>\lambda</math></b>	0,72
<b>Number of phases</b>	3 AC	<b>Offset factor <math>\cos \varphi</math></b>	0,95
<b>Line voltage</b>	380 ... 480 V +10 % -15 %	<b>Efficiency <math>\eta</math></b>	0,98
<b>Line frequency</b>	47 ... 63 Hz	<b>Ambient conditions</b>	
<b>Output</b>		<b>Cooling</b>	Ventilatore esterno
<b>Number of phases</b>	3 AC	<b>Installation altitude</b>	1000 m
<b>Rated voltage</b>	400 V	<b>Ambient temperature</b>	
<b>Rated power (HO)</b>	4,00 kW / 5,00 hp	<b>Operation</b>	-10 ... 60 °C (14 ... 140 °F)
<b>Rated power (LO)</b>	4,00 kW / 5,00 hp	<b>Storage</b>	-40 ... 70 °C (-40 ... 158 °F)
<b>Rated current (HO)</b>	8,80 A	<b>Relative humidity</b>	
<b>Rated current (LO)</b>	8,80 A	<b>Max. operation</b>	95 %
<b>Rated current (HO) at 480V</b>	8,20 A	<b>Communication</b>	
<b>Rated current (LO) at 480V</b>	8,20 A	<b>Communication</b>	USS, Modbus RTU
<b>Pulse frequency</b>	2 kHz	<b>Standards</b>	
<b>Output frequency</b>	0 ... 550 Hz	<b>Compliance with standards</b>	CE, cULus, C-tick, KC
		<b>CE marking</b>	EN 61800-5-1 / EN 60204-1 e EN 61800-3

### Overload capability

#### Low Overload (LO)

110 % corrente di uscita nominale per 60 s, tempo di ciclo 300 s

#### High Overload (HO)

150 % corrente di uscita nominale per 60 s, tempo di ciclo 300 s



Ordering data

6SL3210-5BE24-0UV0

### Mechanical data

Mounting position	Montaggio passante / montaggio a parete / montaggio affiancato
Degree of protection	IP20
Size	FSB
Net weight	1,60 kg
Width	140,0 mm
Height	160,0 mm
Depth	164,5 mm

### Connections

#### Max. motor cable length

Shielded	25 m
Unshielded	50 m

### Inputs/ outputs

#### Standard digital inputs

Number	4
--------	---

#### Digital outputs

Number as relay changeover contact	1
Number as transistor	1

#### Analog inputs

Number	2 (Utilizzabile come ingresso digitale aggiuntivo)
--------	---

#### Analog outputs

Number	1
--------	---